

SUN TV CHANNELS PIRD Tuning procedure – MEASAT M3D 91.5 DEG E

Following are the New frequency parameters kindly Re-Tune to the said frequency (as per attachment titled SUN TV network delivery Parameters).

Procedure to Re-Tune PIRD Harmonic

Step 1. Step 1. Please be ready with new Satellite Measat M3D 91.5 Degree E-Vertical Polarity RF Cable, Input to the Relevant Port.

Step 2. Press Enter Button at the Front panel.

Step 3. Select Input.

Step 4. Select DVB-S/S2 Port -1 –Config

Step 5. Select Satellite Frequency –Change to new **frequency 4040 MHz** to tune Sun TV channels in **Stream 1** (details in attachment titled SUN TV network delivery Parameters).

Step 6. Press ESC button

Step 7. Select Decoding

Step 8. Select Configuration

Step 9. Select Program Selection

Step 10. Select Input program

Step 11. Select Relevant SUN TV Channel for the PIRD .

Step 12. Repeat Process 1 to 7 to tune each Sun TV Network Channel on Stream1 to receive the required Sun Channel on each of the PIRD.

Step 13. To receive SUN TV network channels **on Stream 2** follow steps 1 to 3 and in Step 4 select **frequency 4080 MHZ**.

Step 14. Repeat process Step 5 to Step 12 to complete receiving all Sun TV network Channels.

PLEASE DO NOT REMOVE CAM AND/OR VC CARD FROM THE SLOT